

Pioneer DJ



DJM-5000 In Pursuit Of Perfection

96kHz/24-bit digital audio / 3-way USB audio interface / Master/Zone output / 3 Microphone channels / 4 Microphone effects / Advanced and Normal talk over feature
Sound Maximizer boosts EQ dynamics / Fully Assignable USB-MIDI / Send/Return Terminals



Providing more flexibility, compatibility and possibilities, the powerful 4-channel DJM-5000 delivers many benefits and new innovations for DJs on the move.

Specifications

Number of Channels	4
Input Terminals	CD/Line x 6 (RCA), Digital In x 2 (RCA)
MIC	3 (Top panel XLR + 1/4-inch Phone x 1, XLR x 1, 1/4-inch Phone x 1)
Output Terminals	Master Out x 2 (XLR x 1, RCA x 1) Zone Out x 1 (XLR) Booth Out x 1 (1/4-inch Phone) Headphone Monitor Out x 1 (Top panel 1/4-inch phone) Record Out x 1 (RCA)
Other Terminals	Send x 1 (1/4-inch phone) Return x 1 (1/4-inch phone) Control Out x 2 (3.5 Mini Jack) USB x 1 (USB B Port)
Power Requirements	AC 220-240V (50/60 Hz)
Dimensions (W x D x H)	482.6 x 225.1 x 107.8 mm
Sampling Rate	96 kHz
A/D, D/A Converter	24-bit
Frequency Response	20 Hz - 20 kHz
Total Harmonic Distortion	0.005% or less
Signal-to-Noise Ratio	103 dB (Line)
Head Room	19 dB
Power Consumption	29 W
Weight	6.9 kg



Pioneer Europe N.V. Multimedia Division, Slough SL2 4QP, UK TEL +44 (0) 1753 789789

Demo Videos On

DJSOUNDS.COM

Features and specifications of the products described or illustrated in this catalogue are correct at the time of printing but could change as production changes might occur. This catalogue may contain typographical errors and the colours of the depicted products may deviate slightly from reality. Consult your Pioneer dealer to ensure that actual features and specifications match your requirements. This catalogue may contain references to products that may or will not be available in your country.